

Zero-error capacity of a quantum channel

Rex A. C. Medeiros and Francisco M. de Assis
Federal University of Campina Grande
Department of Electrical Engineering
Av. Aprígio Veloso, 882, Bodocongó, 58109-970
Campina Grande, Paraíba, Brazil
e-mail: [rex,fmarcos]@dee.ufcg.edu.br

The zero-error capacity of a discrete classical channel was first defined by Shannon as the least upper bound of rates for which one transmits information with zero probability of error [C. Shannon, *IRE Trans. Inform. Theory*, IT-2(3):8–19, 1956]. Here, we define the quantum zero-error capacity, a new kind of classical capacity of a noisy quantum channel $\mathcal{C}$ represented by a trace-preserving map (TPM) $\mathcal{E}(\cdot)$. Moreover, the necessary requirement for which a quantum channel has zero-error capacity greater than zero is also given. All proofs will appear in the full paper. Indeed, we will show the connection between quantum zero-error capacity and capacity of a graph.

Let $\mathcal{X}$ be the set of possible input states to the quantum channel $\mathcal{E}(\cdot)$, belonging to a d -dimensional Hilbert space $\mathcal{H}$, and let $\bar{\rho} \in \mathcal{X}$. We denote $\bar{\sigma}_k = \mathcal{E}(\bar{\rho})$ the received quantum state when $\bar{\rho}$ is transmitted through the quantum channel. Because knowledge of post-measurement states is not important, measurements are performed by means of a POVM (Positive Operator-Valued Measurements) $\{E_j\}$, where $\sum_j E_j = I$. Assume that $p(j|i)$ denotes the probability of Bob measures j given that Alice sent the state $\bar{\rho}_i$. Then, $p(j|i) = \text{tr}[\bar{\sigma}_i E_j]$.

We define the zero-error capacity of a quantum channel for product states. A product of any n input states will be called an input quantum codeword, $\rho_i = \bar{\rho}_{i_1} \otimes \cdots \otimes \bar{\rho}_{i_n}$, belonging to a d^n -dimensional Hilbert space $\mathcal{H}^n$. A mapping of K classical messages (which we may take to be the integers $1, \dots, K$) into a subset of input quantum codewords will be called a quantum block code of length n . Thus, $\frac{1}{n} \log K$ will be the rate for this code. A piece of n output indices obtained from measurements performed by means of a POVM $\{E_j\}$ will be called an output word, $w = \{1, \dots, N\}^n$. A decoding scheme for a quantum block code of length n is a function that univocally associates each output word with integers 1 to K representing classical messages. The probability of error for this code is greater than zero if the system identifies a different message from the message sent.

Definition 1 (Zero-error capacity of a quantum channel) Let $\mathcal{E}$ be a trace-preserving quantum map representing a noisy quantum channel. The zero-error capacity for this channel, denoted by $C^0(\mathcal{E})$, is the least upper bound of achievable rates with probability of error equal to zero. That is,

$$C^0(\mathcal{E}) = \sup_n \frac{1}{n} \log K(n), \quad (1)$$

where $K(n)$ stands for the number of classical messages that the system can transmit without error, when a quantum block code of length n is used.

According to the classical definition of zero-error capacity, it is possible to establish a condition for which a quantum has quantum zero-error capacity greater than zero.

Theorem 1 Let $\mathcal{S} = \{\bar{\rho}_i\}$, $\mathcal{S} \subset \mathcal{X}$ be a set of $M \leq d$ quantum states, and let $\mathcal{P} = \{E_j\}$ be a POVM having $N \geq M$ elements such that $\sum_j E_j = I$. Consider the subsets

$$A_k = \{j \in \{1, \dots, N\}; p(j|k) > 0\}; k \in \{1, \dots, M\}. \quad (2)$$

Then, the quantum channel $\mathcal{E}$ has zero-error capacity greater than zero iff there exists a set $\mathcal{S}$ and a POVM $\mathcal{P}$ for which at least one pair $(a, b) \in \{1, \dots, M\}^2$, $a \neq b$, the subsets A_a and A_b are disjoint, i.e., $A_a \cap A_b = \emptyset$.

The respective quantum states $\bar{\rho}_a$ and $\bar{\rho}_b$ are said to be non-adjacent in $\mathcal{E}(\cdot)$ for the POVM $\mathcal{P}$.

Definition 2 (Optimum $(\mathcal{S}, \mathcal{P})$ for $\mathcal{E}(\cdot)$) . Consider the set of pairs $A = \{(a_i, b_i) \in \{1, \dots, M\}^2\}$ for which $A_{a_i} \cap A_{b_i} = \emptyset$. The optimum $(\mathcal{S}, \mathcal{P})$ for $\mathcal{E}(\cdot)$ is composed of a set $\mathcal{S} = \{\bar{\rho}_i\}$ and a POVM $\mathcal{P} = \{E_j\}$ maximizing the cardinality $\|A\|$.

Theorem 2 The zero-error capacity of a noisy quantum channel $\mathcal{E}(\cdot)$ is achieved iff the optimum $(\mathcal{S}, \mathcal{P})$ is used.

At first glance, one may think the Definition 1 is identical to the classical case. However, according with Theorem 2, it turns out that the supremum in Eq. (1) is taken over all sets $\mathcal{S}$ of possible input states $\bar{\rho}$ for the quantum channel $\mathcal{C}$ and all POVM $\{E_j\}$. The restriction on the creation of quantum states means that each state $\bar{\rho}$ can not be entangled with other states across two or more uses of the channel. However, we point that, likewise Holevo-Schumacher-Westmoreland's capacity, the decoding scheme allows measurements entangled across n uses of the channel.